



Proximity Switch– product number 00234

Product characteristic

The Proximity Switch (motion sensor) is designed to be used in KLUS LED Linear fixtures. It is dedicated for switching LED lights “on” and “off” without the need of touching the switch. The bottom of the Proximity switch is equipped with tape that allows secure mounting of the switch and additionally cools down the switch when mounted into an extrusion.

Caution

- * We do not recommend installing the proximity switch above the stove top. Hot air can trigger the sensor.
- * We do not recommend installing the proximity switch near curtains. Drafts of air can move the curtain and as a result trigger the sensor.
- * Do not bend the base of proximity switch as it may damage the device.
- * Switching the main power on/off will cause the lit LED fixtures operated by the proximity switch to be turned “off”.
- * To be used with non-dimmable drivers only

Applications

The Proximity switch is dedicated for applications that require very high hygiene standards such as: laboratories, hospital operating rooms. The switch guaranties safety while turning the light on in the bathroom with wet hands or any other application where you may not physically want to touch the switch. The switch provides comfort for example while working in the kitchen as it allows for quick and secure triggering of lighting during work without having to touch the switch.

Technical specification

Function	switch on/off
Voltage	12 - 24V
Maximum Current	4A, 48W/12V; 98W/24V
Standby Power Consumption	0.02W/12V; 0.04W/24V
Dimensions	43 mm x 11 mm x 3 mm
Detection distance depending on the cover type	3 - 8 cm
Operational temperature range	-20°C ... +55°C
Ready to work	3 seconds after power on

Connection scheme

